# 406-512 MHz

# **VHF/UHF Base Station Duplexers**

## **PD526 Series**

These Celwave units use a total of six pass-reject dual-notch resonators with three resonators per channel as the normal arrangement. They are suitable for many applications other than duplexing and their dual-notch circuitry provides a pseudo band pass characteristic for high Tx-Rx isolation. These units are available with reversible mounting brackets to allow flush rack mounting with connections in the rear. Specify PD526-4-SR or PD526-5-SR. Intercabling is exclusively RG214/U cable.

- **High isolation** Minimizes interference.
- **Temperature compensated** Assures consistent performance across temperature and power range.
- Low insertion loss Maximizes effective radiated power.



### PD526 Series

Order Info	ormation
Item Number	Frequency Range MHz
PD526-WB-SR-1 (@ 5MHz sp	) 406 - 440
PD526-WB-SR-1 (@ 10MHz s	p) 406 - 440
PD526-WB-1(@ 10MHz sp)	406 - 440
PD526-4-SR-1	406 - 470
PD526-4-1	406 - 470
PD526-WB-SR-2 (@ 10MHz s	p) 435 - 470
PD526-WB-2(@ 10MHz sp)	435 - 470
PD526-4-SR-2	435 - 470
PD526-4-2	435 - 470
PD526-5-SR-1	470 - 490
PD526-5-1	470 - 490
PD526-5-SR-2	490 - 512
PD526-5-2	490 - 512

This document may not, in whole or in part, be copied, reproduced, translated, or reduced to any electronic medium or machine-readable form without prior consent in writing from Celwave<sup>®</sup>. The product specifications and data presented in this catalog are subject to change without notice. All product information is believed to be accurate at time of distribution, but Celwave shall not be responsible for printing or typographical errors.

# **VHF/UHF Base Station Duplexers**

ELECTRICAL SPECIFICATIONS	PD526-WB-SR-1 (@ 5MHz sp)	PD526-WB-SR-1 (@ 10MHz sp)	PD526-WB-SR-2 (@ 10MHz sp)	PD526-WB-1 (@ 10MHz sp)
Frequency Range - MHz	406-440	406-440	435-470	406-440
Frequency Spacing, Min MHz	5	10	10	10
Tx Bandwidth - MHz	1.2 (Note 1)	1.2 (Note 1)	1.2 (Note 1)	1.2 (Note 1)
Rx Bandwidth - MHz	1.2 (Note 1)	1.2 (Note 1)	1.2 (Note 1)	1.2 (Note 1)
Continuous Power Input, Max Watts	150	200	200	200
Insertion Loss, Tx - Ant dB	1.2	1.0	1.0	1.0
Insertion Loss, Rx - Ant dB	1.2	1.0	1.0	1.0
Tx Noise Suppression at Rx Frequency - dB	80	100	100	100
Rx Isolation at at Tx Frequency - dB	80	100	100	100
VSWR, Max. (50 ohms)	1.3:1	1.3:1	1.3:1	1.3:1
Connectors - Ant. Port	N-female	N-female	N-female	N-female
- Tx Port	N-female	N-female	N-female	N-female
- Rx Port	N-female	N-female	N-female	N-female
Temperature Range - °C	-30 to +60	-30 to +60	-30 to +60	-30 to +60

#### **MECHANICAL SPECIFICATIONS**

Height - in. (mm)	5-1/4(133)	5-1/4(133)	5-1/4(133)	5-1/4(133)
Width - in. (mm)	19(483)	19(483)	19(483)	19(483)
Depth - in. (mm)	14(356)	14(356)	14(356)	14(356)
Mounts in 19" (483mm) EIA Rack (Yes/No)	Yes	Yes	Yes	Yes
Weight - Ibs. (kg)	23(10.5)	23(10.5)	23(10.5)	23(10.5)
Nata 4. Destances also for the second file and	والمراجع والم	al Canadit Analizations Fasi		

Note 1: Performance shown for the specific spacing and bandwidth listed. Consult Applications Engineering for performance at other spacings

ELECTRICAL SPECIFICATIONS	PD526-WB-2 (@ 10MHz sp)	PD526-4-SR-1	PD526-4-SR-2	PD526-4-1
Frequency Range - MHz	435-470	406-470	435-470	406-470
Frequency Spacing, Min MHz	10	3	3	3
Tx Bandwidth - MHz	1.2 (Note 1)	0.025	0.025	0.025
Rx Bandwidth - MHz	1.2 (Note 1)	0.025	0.025	0.025
Continuous Power Input, Max Watts	200	250	250	250
Insertion Loss, Tx - Ant dB	1.0	1.0	1.0	1.0
Insertion Loss, Rx - Ant dB	1.0	1.0	1.0	1.0
Tx Noise Suppression at Rx Frequency - dB	100	100	100	100
Rx Isolation at at Tx Frequency - dB	100	100	100	100
VSWR, Max. (50 ohms)	1.3:1	1.3:1	1.3:1	1.3:1
Connectors - Ant. Port	N-female	N-female	N-female	N-female
- Tx Port	N-female	N-female	N-female	N-female
- Rx Port	N-female	N-female	N-female	N-female
Temperature Range - °C	-30 to +60	-30 to +60	-30 to +60	-30 to +60

#### **MECHANICAL SPECIFICATIONS**

Height - in. (mm)	5-1/4(133)	5-1/4(133)	5-1/4(133)	5-1/4(133)
Width - in. (mm)	19(483)	19(483)	19(483)	19(483)
Depth - in. (mm)	14(356)	14(356)	14(356)	14(356)
Mounts in 19" (483mm) EIA Rack (Yes/No)	Yes	Yes	Yes	Yes
Weight - Ibs. (kg)	23(10.5)	23(10.5)	23(10.5)	23(10.5)

Note 1: Performance shown for the specific spacing and bandwidth listed. Consult Applications Engineering for performance at other spacings.

Celwave, 2 Ryan Road, Marlboro, NJ 07746-1899 • 1(800) CELWAVE (732) 462-1880 • www.rfsworld.com

This document may not, in whole or in part, be copied, reproduced, translated, or reduced to any electronic medium or machine-readable form without prior consent in writing from Celwave<sup>6</sup>. The product specifications and data presented in this catalog are subject to change without notice. All product information is believed to be accurate at time of distribution, but Celwave shall not be responsible for printing or typographical errors.


# **VHF/UHF Base Station Duplexers**


ELECTRICAL SPECIFICATIONS	PD526-4-2	PD526-5-SR-1	PD526-5-SR-2	PD526-5-1
Frequency Range - MHz	435-470	470-490	490-512	470-490
Frequency Spacing, Min MHz	3	3	3	3
Tx Bandwidth - MHz	0.025	0.025	0.025	0.025
Rx Bandwidth - MHz	0.025	0.025	0.025	0.025
Continuous Power Input, Max Watts	250	250	250	250
Insertion Loss, Tx - Ant dB	1.0	1.0	1.0	1.0
Insertion Loss, Rx - Ant dB	1.0	1.0	1.0	1.0
Tx Noise Suppression at Rx Frequency - dB	100	100	100	100
Rx Isolation at at Tx Frequency - dB	100	100	100	100
VSWR, Max. (50 ohms)	1.3:1	1.3:1	1.3:1	1.3:1
Connectors - Ant. Port	N-female	N-female	N-female	N-female
- Tx Port	N-female	N-female	N-female	N-female
- Rx Port	N-female	N-female	N-female	N-female
Temperature Range - °C	-30 to +60	-30 to +60	-30 to +60	-30 to +60
MECHANICAL SPECIFICATIONS				
Height - in. (mm)	5-1/4(133)	5-1/4(133)	5-1/4(133)	5-1/4(133)
Width - in. (mm)	19(483)	19(483)	19(483)	19(483)
Depth - in. (mm)	14(356)	14(356)	14(356)	14(356)
Mounts in 19" (483mm) EIA Rack (Yes/No)	Yes	Yes	Yes	Yes
Weight - Ibs. (kg)	23(10.5)	23(10.5)	23(10.5)	23(10.5)
ELECTRICAL SPECIFICATIONS	PD526-5-2			
Frequency Range - MHz	490-512			
Frequency Spacing, Min MHz	3			
Tri Danahurakh Mila	0.005			

inequency range minz	400 012	
Frequency Spacing, Min MHz	3	
Tx Bandwidth - MHz	0.025	
Rx Bandwidth - MHz	0.025	
Continuous Power Input, Max Watts	250	
Insertion Loss, Tx - Ant dB	1.0	
Insertion Loss, Rx - Ant dB	1.0	
Tx Noise Suppression at Rx Frequency - dB	100	
Rx Isolation at at Tx Frequency - dB	100	
VSWR, Max. (50 ohms)	1.3:1	
Connectors - Ant. Port	N-female	
- Tx Port	N-female	
- Rx Port	N-female	
Temperature Range - °C	-30 to +60	


### **MECHANICAL SPECIFICATIONS**

Height - in. (mm)	5-1/4(133)	
Width - in. (mm)	19(483)	
Depth - in. (mm)	14(356)	
Mounts in 19" (483mm) EIA Rack (Yes/No)	Yes	
Weight - Ibs. (kg)	23(10.5)	





PDS26 RESPONSE CURVES (Typical) 3 MHz SPACING (406-512 MHz)



### Celwave, 2 Ryan Road, Marlboro, NJ 07746-1899 • 1(800) CELWAVE (732) 462-1880 • www.rfsworld.com

This document may not, in whole or in part, be copied, reproduced, translated, or reduced to any electronic medium or machine-readable form without prior consent in writing from Celwave<sup>®</sup>. The product specifications and data presented in this catalog are subject to change without notice. All product information is believed to be accurate at time of distribution, but Celwave shall not be responsible for printing or typographical errors.